

Refer to the xPONENT® for MAGPIX® Software User Manual for detailed instructions, precautions, and warnings.

For Research Use Only. Not for use in diagnostic procedures.

Luminex Corporation

12212 Technology Boulevard
Austin, Texas 78727-6115
U.S.A.
Phone: 512-219-8020
Fax: 512-219-5195

Technical Support

Email: support@luminexcorp.com
Phone: 512-381-4397
Toll-free: 1-877-785-2323
International: + 800-2939-4959

xPONENT® for MAGPIX® Quick Guide

PN 89-30000-00-232 Rev. H
February 2015

Luminex Corporation (Luminex) reserves the right to modify its products and services at any time. This guide is subject to change without notice. Although prepared to ensure accuracy, Luminex assumes no liability for errors or omissions, or for any damages resulting from the application or use of this information.

The following are trademarks of Luminex Corporation: Luminex®, xPONENT®, and MAGPIX®.

All other trademarks are trademarks of their respective companies.

Luminex

Quick Guide

xPONENT® for MAGPIX®



Luminex For a copy of the MSDS/SDS, visit: www.luminexcorp.com

© 2010 - 2015 Luminex Corporation. All rights reserved. No part of this publication may be reproduced, transmitted, transcribed, or translated into any language or computer language, in any form or by any means without prior express, written consent of Luminex Corporation.

Defining the System Initialization Routine

NOTE: Luminex recommends weekly calibration and daily performance verification of the MAGPIX system. You can set up the system initialization routine to include calibration and verification on the **Admin** page, **System Setup** tab, **Maintenance Options** section.

1. Open the **Admin** page.
2. Click the **System Setup** tab.
3. Under **Maintenance Options**, choose **Fluidics prep, performance verification** from the drop-down menu.
4. Click **Save**.

Running the System Initialization Routine

1. On the **Home** page, click **System Initialization** under **Daily Activities**. The **Auto Maint** tab displays.

NOTE: If the instrument has not been calibrated, **Calibration Verification** will be defaulted on the **Auto Maint** tab. If the instrument has been calibrated, the **Automated Maintenance Option**, as defined, on the **Admin** page will be highlighted.

2. Verify that the correct reagents have been added to the correct reservoir or well.
3. Click **Retract**.
4. Click **Run**.

Shutting Down the MAGPIX®

1. On the **Home** page, click **Shutdown**. The **Auto Maint** tab opens with **System Shutdown** selected.

2. Click **Eject**.

3. Fill reservoir **RA1** with 3/4 of DI water.

4. Fill reservoir **RC1** with 3/4 of 10% to 20% household bleach solution.

5. Verify that reservoir **RD1** is empty.

6. Click **Retract**, then click **Run**.

Running a Post-Batch Routine

NOTE: Luminex recommends running the default Post-Batch routine with 0.1N NaOH after every batch to clean the sample chamber and maintain peak performance. If the default Post-Batch routine is turned off, the Post-Batch routine can be manually executed from the Commands & Routines (**Cmds & Routines**) tab in the **Maintenance** page.

1. Open the **Maintenance** page.

2. Click the **Cmds & Routines** tab.

3. Choose the **Post-Batch Routine (Luminex)** from the Routine Name drop-down menu.

4. These are the required reagents:
 - Soak: DI water in **RA1**
 - Sanitize: IPA in **RB1**
 - Clean: 0.1N NaOH in **RC1**